IN THE CLAIMS:

Please amend the claims as indicated below:

1.   (Currently Amended) A method for compensating for polarization mode dispersion in an optical fiber communication system, comprising the steps of:

5   reducing said polarization mode dispersion using a cascade of two-port all-pass filters; and

                adjusting coefficients of said two-port all-pass filters using a least mean square algorithm, wherein said adjusting step is performed by a device.

10   2.   (Previously Presented) The method of claim 1, wherein said cascade of two-port all-pass filters comprises a two-channel structure consisting of multiple cascades of all-pass filters and directional couplers.

3.   (Original) The method of claim 1, wherein said coefficient values are adjusted to 15   minimize a cost function.

4.   (Original) The method of claim 1, further comprising the step of measuring said polarization mode dispersion in a received optical signal.

20   5.   (Original) The method of claim 4, wherein said measuring step employs a tunable narrowband optical filter to render information from energy detector measurements.

6.   (Previously Presented) The method of claim 1, wherein said cascade of two-port all-pass filters comprises a first all-pass filter A having a vector a comprised of P coefficients and 25   a second all-pass filter B having a vector b comprised of Q coefficients and wherein said least mean square algorithm adjusts said coefficients as follows:

$$w(n+1) = w(n) - \mu \nabla(J),$$

where n indicates the current iteration number and w is a composite coefficient vector defined as:

$$w = \begin{bmatrix} a \\ b \end{bmatrix}, \ \nabla(J) \equiv \begin{bmatrix} \dfrac{\partial J}{\partial a^T} & \dfrac{\partial J}{\partial b^T} \end{bmatrix}^T$$

is the $(P+Q) \times 1$ complex gradient of J with respect to w and T indicates a transpose operation, and

$$\frac{\partial J}{\partial a^{T}} \equiv \left[\begin{array}{cccc} \dfrac{\partial J}{\partial a_{1}} & \dfrac{\partial J}{\partial a_{2}} & K & \dfrac{\partial J}{\partial a_{P}} \end{array} \right], \text{ and}$$

$$\frac{\partial J}{\partial b^{T}} \equiv \left[\begin{array}{cccc} \dfrac{\partial J}{\partial b_{1}} & \dfrac{\partial J}{\partial b_{2}} & K & \dfrac{\partial J}{\partial b_{Q}} \end{array} \right].$$

5

7.　　　　(Currently Amended) A method for compensating for polarization mode dispersion in an optical fiber communication system, comprising the steps of:

　　　　reducing said polarization mode dispersion using a cascade of two-port all-pass filters; and

10　　　　adjusting coefficients of said two-port all-pass filters using a Newton algorithm, wherein said adjusting step is performed by a device.

8.　　　　(Previously Presented) The method of claim 7, wherein said cascade of two-port all-pass filters comprises a two-channel structure consisting of multiple cascades of all-pass 15　filters and directional couplers.

9.　　　　(Original) The method of claim 7, wherein said coefficient values are adjusted to minimize a cost function.

20　10.　　　　(Original) The method of claim 7, further comprising the step of measuring said polarization mode dispersion in a received optical signal.

11.　　　　(Original) The method of claim 10, wherein said measuring step employs a tunable narrowband optical filter to render information from energy detector measurements.

25

12.　　　　(Previously Presented) The method of claim 7, wherein said cascade of two-port all-pass filters comprises a first all-pass filter A having a vector a comprised of P coefficients and a second all-pass filter B having a vector b comprised of Q coefficients and wherein said Newton algorithm adjusts said coefficients as follows:

$$w(n+1) = w(n) - \mu H^{-1}\nabla(J)$$

where n indicates the current iteration number and w is a composite coefficient vector defined as:

$$w = \begin{bmatrix} a \\ b \end{bmatrix}, \quad \nabla(J) \equiv \begin{bmatrix} \dfrac{\partial J}{\partial a^T} & \dfrac{\partial J}{\partial b^T} \end{bmatrix}^T$$

$$\frac{\partial J}{\partial a^T} \equiv \begin{bmatrix} \dfrac{\partial J}{\partial a_1} & \dfrac{\partial J}{\partial a_2} & K & \dfrac{\partial J}{\partial a_P} \end{bmatrix}, \text{ is the } (P+Q)\times 1 \text{ complex gradient of } J \text{ with respect to } w, \text{ T}$$

5   indicates a transpose operation and, a Hessian matrix, H, is defined as follows:

$$H = \frac{\partial^2 J}{\partial w \partial w^T} = \begin{bmatrix} \dfrac{\partial^2 J}{\partial a \partial a^T} & \dfrac{\partial^2 J}{\partial a \partial b^T} \\ \dfrac{\partial^2 J}{\partial b \partial a^T} & \dfrac{\partial^2 J}{\partial b \partial b^T} \end{bmatrix} \text{ and}$$

$$\frac{\partial J}{\partial b^T} \equiv \begin{bmatrix} \dfrac{\partial J}{\partial b_1} & \dfrac{\partial J}{\partial b_2} & K & \dfrac{\partial J}{\partial b_Q} \end{bmatrix}.$$

13.   (Currently Amended) A polarization mode dispersion compensator in an optical

10   fiber communication system, comprising:

a cascade of two-port all-pass filters having coefficients that are adjusted using a

least mean square algorithm, wherein said adjustment is performed by a device.

14.   (Previously Presented) The polarization mode dispersion compensator of claim

15   13, wherein said cascade of two-port all-pass filters comprises a two-channel structure consisting

of multiple cascades of all-pass filters and directional couplers.

15.   (Original) The polarization mode dispersion compensator of claim 13, wherein

said coefficient values are adjusted to minimize a cost function.

20

16.   (Previously Presented) The polarization mode dispersion compensator of claim

13, further comprising a polarization mode dispersion measuring device for measuring said

polarization mode dispersion in a received optical signal.

17.   (Previously Presented) The polarization mode dispersion compensator of claim 16, wherein said polarization mode dispersion measuring device employs a tunable narrowband optical filter to render information from energy detector measurements.

5   18.   (Currently Amended) A polarization mode dispersion compensator in an optical fiber communication system, comprising:

    a cascade of two-port all-pass filters having coefficients that are adjusted using a Newton algorithm, wherein said adjusting step is performed by a device.

10   19.   (Previously Presented) The polarization mode dispersion compensator of claim 18, wherein said cascade of two-port all-pass filters comprises a two-channel structure consisting of multiple cascades of all-pass filters and directional couplers.

20.   (Original) The polarization mode dispersion compensator of claim 18, wherein

15   said coefficient values are adjusted to minimize a cost function.

21.   (Previously Presented) The polarization mode dispersion compensator of claim 18, further comprising a polarization mode dispersion measuring device for measuring said polarization mode dispersion in a received optical signal.

20

22.   (Previously Presented) The polarization mode dispersion compensator of claim 21, wherein said polarization mode dispersion measuring device employs a tunable narrowband optical filter to render information from energy detector measurements.

25